

Technical Advisory Notice: Manual connex Firmware Update Instructions X12 & X16
TA071022 v2

NOTE – The instructions are in 2 parts.

Merrychef[®] always strives to improve its products based on customer feedback and data.

A new firmware version has been released – version 1.5.5b, this can be downloaded from the link below.

<https://assets.welbilt.com/share/55BE6BD7-FF99-4E0C-901C0B7FBCBF68EE/>

 **MERRYCHEF**
CONNEX FIRMWARE UPDATE



Firmware Version: 1.5.5b

Urgency: High – Immediate Update

Changes to previous version:


- 1) The cooling fans now stay off (as long as the oven cavity is below 50C) when the oven is in standby mode.
- 2) Factory set up will not lose data when the ovens are power cycled.
- 3) Timeout is changed to 15 minutes when performing firmware updates to avoid false errors being generated.



Part 1 - Firmware Download Instructions

NOTE – You will need a blank “formatted” USB key / pen drive.

- Download the firmware from the link above by copying it into your browser.
- Ensure the filename is called **welbilt-firmware-imx6xsabresd.tar** and rename the file if necessary, for example, remove any numbers and brackets such as (3) that may have been added during the windows download process.
- Save the zipped file to your desktop.
- Make a new folder on the USB called **welbilt** (all lower case).
- Create a new folder called **firmware** (all lower case) inside the **welbilt** folder. (see below)
 - Go to the saved zipped file on desktop and right click and select extract all to the USB device
- Move the unzipped file into the firmware folder.
- You are now ready to update the firmware on the oven.



Please turn over for Part-2 – Firmware Update Instructions

Part 2 - Firmware Update Instructions

NOTE- It will take approximately 17 Minutes to complete the update process.

- Isolate the oven from the mains power supply.
- Insert the USB into the slot next to the air filter behind the compartment
- Reconnect the oven to the mains power supply.


- Wait for the power button to appear on the screen.



- Select settings.



- Enter the password – **MANAGER (All upper case) or the full serial number.**
- Select updates.



- Wait for the Update UI Firmware button to turn from Grey to White.



- Select the Update UI Firmware button.
- The screen will say Updating...
- The screen will then shut down and turn Black.
- The screen will then come back on and say Loading.
- The screen will then say Initialising.
- The screen will then say Updating.
- The screen will then say IO controller is being restarted.
- The screen will then shut down and turn Black.
- Tap the screen to wake it up from sleep mode.
- Select the Info button.
- Check the oven has updated successfully.
- **Check – UI version 1.5.5b**
- **Check – IO version 000.008.070**
- Remove the USB.
- Check the time & date and correct if required.
- Run a recommission test.
- Let the oven heat up.
- Run a test cook.